10V Drive Nch MOSFET

RDD050N20

Structure

Silicon N-channel **MOSFET**


● Features

- 1) Low on-resistance.
- 2) Low input capacitance.
- 3) Exellent resistance to damage from static electricity.

Application

Switching

●Dimensions (Unit:mm)



Packaging specifications

	Package	Taping
Type	Code	TL
	Basic ordering unit (pieces)	2500
RDD050N20		0


● Absolute maximum ratings (Ta=25°C)

Parameter		Symbol	Limits	Unit
Drain-Source Voltage		V _{DSS}	200	V
Gate-Source Voltage		Vgss	±30	V
Drain Current	Continuous	ID	±5	Α
Drain Current	Pulsed	I _{DP} *1	±20	Α
Source Current (Body Diode)	Continuous	Is	5	Α
	Pulsed	I _{SP} *1	20	Α
Avalanche Current		I _{AS} *2	5	Α
Avalanche Energy		E _{AS} *2	75	mJ
Total Power Dissipation (Tc=25°C)		P _D	20	W
Channel Temperature		Tch	150	°C
Storage Temperature		Tstg	-55 to +150	°C

Thermal resistance

Parameter	Symbol	Limits	Unit
Channel to case	Rth(ch-c)	6.25	°C/W

●Equivalent Circuit



*A protection diode is included between the gate and the source terminals to protect the diode against static electricity when the product is in use. Use the protection circuit when the fixed voltages are exceeded.

^{*1} Pw ≤ 10μs, Duty cycle ≤ 1% *2 L≒ 4.5mH, V_{DD}=50V, R_S=25Ω, 1Pulse, Tch=25°C

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Gate-Source Leakage	Igss	_	_	±10	μΑ	Vgs=±30V, Vps=0V
Drain-Source Breakdown Voltage	V(BR) DSS	200	_	_	V	In=1mA, Vgs=0V
Zero Gate Voltage Drain Current	IDSS	_	_	25	μΑ	V _{DS} =200V, V _{GS} =0V
Gate Threshold Voltage	VGS (th)	2.0	_	4.0	V	VDS=10V, ID=1mA
Static Drain-Source On-State Resistance	RDS (on)	_	0.55	0.72	Ω	Ib=2.5A, Vgs=10V
Forward Transfer Admittance	Yfs *	1.1	1.8	_	S	Vps=10V, Ip=2.5A
Input Capacitance	Ciss	_	292	_	pF	Vps=10V
Output Capacitance	Coss	_	92	_	pF	V _{GS} =0V
Reverse Transfer Capacitance	Crss	_	28	_	pF	f=1MHz
Turn-On Delay Time	td (on) *	_	10	_	ns	ID=2.5A, VDD ≒100V
Rise Time	tr *	_	22	_	ns	V _{GS} =10V
Turn-Off Delay Time	td (off) *	_	23	_	ns	RL=40Ω
Fall Time	t _f *	_	28	_	ns	R _G =10Ω
Total Gate Charge	Qg *	_	9.3	_	nC	V _{DD} =100V
Gate-Source Charge	Qgs *	_	2.8	_	nC	V _G s=10V
Gate-Drain Charge	Q _{gd} *	_	3.7	_	nC	ID=5A

^{*} Pulsed

●Body diode characteristics (Source-drain) (Ta=25°C)

Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Forward voltage	Vsp *	_	-	1.5	V	I _S = 5.0A, V _{GS} =0V
Reverse recovery time	trr	_	117	_	ns	IDR= 5.0A, VGS=0V
Reverse recovery charge	Qrr	-	0.37	_	μС	di/dt= 100A / μs

^{*} Pulsed

Electrical characteristic curves




Fig.1 Maximum Safe Operating Area




Fig.2 Typical Output Characteristics




Fig.3 Typical Transfer Characteristics




Fig.4 Gate Threshold Voltage vs. Channel Temperature




Fig.5 Static Drain-Source On-State Resistance vs. Drain Current




Fig.6 Static Drain-Source On-State Resistance vs. Gate-Source Voltage




Fig.7 Static Drain-Source On-State Resistance vs. Channel Temperature




Fig.8 Forward Transfer Admittance vs. Drain Current




Fig.9 Reverse Drain Current vs. Source-Drain Voltage




Fig.10 Typical Capacitance vs. Drain-Source Voltage




Fig.11 Dynamic Input Characteristics




Fig.12 Reverse Recovery Time vs. Reverse Drain Current




Fig.13 Switching Characteristcs

•Switching characteristics measurement circuit




Fig.1-1 Switching time measurement circuit




Fig.1-2 Switching waveforms




Fig.2-1 Gate charge measurement circuit




Fig.2-2 Gate charge waveform




Fig.3-1 Avalanche measurement circuit




Fig.3-2 Avalanche waveform

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any
 means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the
 product described in this document are for reference only. Upon actual use, therefore, please request
 that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard
 use and operation. Please pay careful attention to the peripheral conditions when designing circuits
 and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or
 otherwise dispose of the same, no express or implied right or license to practice or commercially
 exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

It is our top priority to supply products with the utmost quality and reliability. However, there is always a chance of failure due to unexpected factors. Therefore, please take into account the derating characteristics and allow for sufficient safety features, such as extra margin, anti-flammability, and fail-safe measures when designing in order to prevent possible accidents that may result in bodily harm or fire caused by component failure. ROHM cannot be held responsible for any damages arising from the use of the products under conditions out of the range of the specifications or due to non-compliance with the NOTES specified in this catalog.

Thank you for your accessing to ROHM product informations.

More detail product informations and catalogs are available, please contact your nearest sales office.

ROHM Customer Support System

THE AMERICAS / EUPOPE / ASIA / JAPAN

www.rohm.com

Contact us : webmaster@rohm.co.jp

Copyright © 2007 ROHM CO.,LTD.

ROHM CO., LTD. 21, Saiin Mizosaki-cho, Ukyo-ku, Kyoto 615-8585, Japan

oan TEL:+81-75-311-2121 FAX:+81-75-315-0172

