TOSHIBA Field Effect Transistor Silicon N Channel MOS Type (U-MOSIV)

TPCA8024

Lithium-Ion Battery Applications Notebook PC Applications Portable Equipment Applications

- Small footprint due to a small and thin package
- Low drain-source ON-resistance: R_{DS} (ON) = 3.5 m Ω (typ.)
- High forward transfer admittance: $|Y_{fs}| = 72 \text{ S} (typ.)$
- Low leakage current: $I_{DSS} = 10 \ \mu A \ (max) \ (V_{DS} = 30 \ V)$
- Enhancement mode: $V_{th} = 1.3$ to 2.5 V ($V_{DS} = 10$ V, $I_D = 1$ mA)

Absolute Maximum Ratings (Ta = 25°C)


Character	ristics	Symbol	Rating	Unit
Drain-source voltage		V _{DSS}	30	V
Drain-gate voltage (R	l _{GS} = 20 kΩ)	V _{DGR}	30	V
Gate-source voltage		V _{GSS}	±20	V
Drain current	DC (Note 1)	ID	35	А
	Pulse (Note 1)	I _{DP}	105	А
Drain power dissipati	on (Tc=25°C)	PD	35	W
Drain power dissipation	on (t = 10 s) (Note 2a)	PD	2.8	W
Drain power dissipation	on (t = 10 s) (Note 2b)	PD	1.6	W
Single pulse avalanch	ne energy (Note 3)	E _{AS}	159	mJ
Avalanche current		I _{AR}	35	А
Repetitive avalanche (1	energy ⁻ c=25°C) (Note 4)	E _{AR}	3.5	mJ
Channel temperature		T _{ch}	150	°C
Storage temperature	range	T _{stg}	-55 to 150	°C

Note: For Note 1 to 4, refer to the next page.

test report and estimated failure rate, etc).


Using continuously under heavy loads (e.g. the application of high temperature/current/voltage and the significant change in temperature, etc.) may cause this product to decrease in the reliability significantly even if the operating conditions (i.e. operating temperature/current/voltage, 1 2 3 4 etc.) are within the absolute maximum ratings. Please design the appropriate reliability upon reviewing the Toshiba Semiconductor Reliability Handbook ("Handling Precautions"/"Derating Concept and Methods") and individual reliability data (i.e. reliability

This transistor is an electrostatic-sensitive device. Handle with care.



Weight: 0.069 g (typ.)

Circuit Configuration




Unit: mm

TOSHIBA

Thermal Characteristics

Characteristics	Symbol	Max	Unit
Thermal resistance, channel to case (Tc=25°C)	R _{th (ch-c)}	3.57	°C/W
Thermal resistance, channel to ambient $(t = 10 \ s)$ (Note 2a)	R _{th (ch-a)}	44.6	°C/W
Thermal resistance, channel to ambient (t = 10 s) (Note 2b)	R _{th (ch-a)}	78.1	°C/W


Marking (Note 5)





Note 1: Ensure that the channel temperature does not exceed 150°C.

Note 2:

(a) Device mounted on a glass-epoxy board (a)







Note 3: $V_{DD} = 24 \text{ V}, \text{ T}_{ch} = 25^{\circ}\text{C}$ (initial), L = 0.1mH, R_G = 25 Ω , I_{AR} = 35 A

Note 4: Repetitive rating: pulse width limited by max channel temperature

Note 5: * Weekly code: (Three digits)



Week of manufacture (01 for the first week of the year, continuing up to 52 or 53) - Year of manufacture (The last digit of the year)


Electrical Characteristics (Ta = 25°C)

Characteristics		Symbol	Test Condition	Min	Тур.	Max	Unit
Gate leakage cur	rrent	I _{GSS}	$V_{GS}=\pm 20~V,~V_{DS}=0~V$			±100	nA
Drain cut-OFF cu	ırrent	I _{DSS}	$V_{DS} = 30 \text{ V}, \text{ V}_{GS} = 0 \text{ V}$	_		10	μA
Drain gourge bro	akdawa valtaga	V (BR) DSS	I _D = 10 mA, V _{GS} = 0 V	30			v
Drain-source brea	akuown vollage	V (BR) DSX	$I_{D} = 10 \text{ mA}, V_{GS} = -20 \text{ V}$	10	$\begin{array}{c ccccc} & - & \pm 100 \\ \hline - & - & 10 \\ \hline 30 & - & - \\ 10 & - & - \\ 10 & - & - \\ 10 & - & - \\ \hline 13 & - & 2.5 \\ \hline - & 5.4 & 7.8 \\ \hline - & 3.5 & 4.3 \\ \hline 36 & 72 & - \\ \hline - & 1800 & - \\ \hline - & 1800 & - \\ \hline - & 1800 & - \\ \hline - & 570 & - \\ \hline - & 111 & - \\ \hline - & 111 & - \\ \hline - & 119 & - \\ \hline - & 22 & - \\ \hline - & 64 & - \\ \hline - & 45 & - \\ \hline \end{array}$	v	
Gate threshold vo	oltage	V _{th}	$V_{DS} = 10 \text{ V}, \text{ I}_{D} = 1 \text{ mA}$	1.3		2.5	V
Drain-source ON-resistance Forward transfer admittance		R _{DS (ON)}	$V_{GS} = 4.5 \text{ V}, \text{ I}_{D} = 17 \text{ A}$	_	5.4	7.8	mΩ
			V _{GS} = 10 V, I _D = 17 A	_	3.5	4.3	
Forward transfer admittance		Y _{fs}	V _{DS} = 10 V, I _D = 17 A	36	72		S
Input capacitance		C _{iss}	$V_{DS} = 10 \text{ V}, \text{ V}_{GS} = 0 \text{ V}, \text{ f} = 1 \text{ MHz}$	_	1800		pF
Reverse transfer capacitance		C _{rss}		_	370		
Reverse transfer capacitance Output capacitance		C _{oss}		_	570		
$ \begin{array}{c c c c c c c c c c c c c c c c c c c $	Rise time	tr	10.V 🗖 🖢 = 17.A	_	11	_	
	19		20				
	Fall time	t _f		_	22	_	- ns
	Turn-off time	t _{off}		_	64	_	
		Qg	V _{DD} ≈ 24 V, V _{GS} = 10 V,	_	45	_	nC
Gate-source charge 1		Q _{gs1}	I _D = 35 A		8		
Gate-drain ("miller") charge		Q _{gd}]		15	—	

Source-Drain Ratings and Characteristics (Ta = 25°C)

Characteristics		Symbol	Test Condition	Min	Тур.	Max	Unit	
Drain reverse current	Pulse	(Note 1)	I _{DRP}	—	—	_	105	А
Forward voltage (diode)			V _{DSF}	$I_{DR} = 35 \text{ A}, V_{GS} = 0 \text{ V}$	_		-1.2	V

TOSHIBA



2010-01-05

100

10

1

Drain current ID (A)

100


10


Drain current ID (A)


1


0.1


TOSHIBA























RESTRICTIONS ON PRODUCT USE

- Toshiba Corporation, and its subsidiaries and affiliates (collectively "TOSHIBA"), reserve the right to make changes to the information in this document, and related hardware, software and systems (collectively "Product") without notice.
- This document and any information herein may not be reproduced without prior written permission from TOSHIBA. Even with TOSHIBA's written permission, reproduction is permissible only if reproduction is without alteration/omission.
- Though TOSHIBA works continually to improve Product's quality and reliability, Product can malfunction or fail. Customers are responsible for complying with safety standards and for providing adequate designs and safeguards for their hardware, software and systems which minimize risk and avoid situations in which a malfunction or failure of Product could cause loss of human life, bodily injury or damage to property, including data loss or corruption. Before customers use the Product, create designs including the Product, or incorporate the Product into their own applications, customers must also refer to and comply with (a) the latest versions of all relevant TOSHIBA information, including without limitation, this document, the specifications, the data sheets and application notes for Product and the precautions and conditions set forth in the "TOSHIBA Semiconductor Reliability Handbook" and (b) the instructions for the application with which the Product will be used with or for. Customers are solely responsible for all aspects of their own product design or applications; (b) evaluating and determining the applicability of any information contained in this document, or in charts, diagrams, programs, algorithms, sample application circuits, or any other referenced documents; and (c) validating all operating parameters for such designs and applications. TOSHIBA ASSUMES NO LIABILITY FOR CUSTOMERS' PRODUCT DESIGN OR APPLICATIONS.
- Product is intended for use in general electronics applications (e.g., computers, personal equipment, office equipment, measuring equipment, industrial robots and home electronics appliances) or for specific applications as expressly stated in this document. Product is neither intended nor warranted for use in equipment or systems that require extraordinarily high levels of quality and/or reliability and/or a malfunction or failure of which may cause loss of human life, bodily injury, serious property damage or serious public impact ("Unintended Use"). Unintended Use includes, without limitation, equipment used in nuclear facilities, equipment used in the aerospace industry, medical equipment, equipment used for automobiles, trains, ships and other transportation, traffic signaling equipment, equipment used to control combustions or explosions, safety devices, elevators and escalators, devices related to electric power, and equipment used in finance-related fields. Do not use Product for Unintended Use unless specifically permitted in this document.
- Do not disassemble, analyze, reverse-engineer, alter, modify, translate or copy Product, whether in whole or in part.
- Product shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any
 applicable laws or regulations.
- The information contained herein is presented only as guidance for Product use. No responsibility is assumed by TOSHIBA for any infringement of patents or any other intellectual property rights of third parties that may result from the use of Product. No license to any intellectual property right is granted by this document, whether express or implied, by estoppel or otherwise.
- ABSENT A WRITTEN SIGNED AGREEMENT, EXCEPT AS PROVIDED IN THE RELEVANT TERMS AND CONDITIONS OF SALE FOR PRODUCT, AND TO THE MAXIMUM EXTENT ALLOWABLE BY LAW, TOSHIBA (1) ASSUMES NO LIABILITY WHATSOEVER, INCLUDING WITHOUT LIMITATION, INDIRECT, CONSEQUENTIAL, SPECIAL, OR INCIDENTAL DAMAGES OR LOSS, INCLUDING WITHOUT LIMITATION, LOSS OF PROFITS, LOSS OF OPPORTUNITIES, BUSINESS INTERRUPTION AND LOSS OF DATA, AND (2) DISCLAIMS ANY AND ALL EXPRESS OR IMPLIED WARRANTIES AND CONDITIONS RELATED TO SALE, USE OF PRODUCT, OR INFORMATION, INCLUDING WARRANTIES OR CONDITIONS OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, ACCURACY OF INFORMATION, OR NONINFRINGEMENT.
- Do not use or otherwise make available Product or related software or technology for any military purposes, including without
 limitation, for the design, development, use, stockpiling or manufacturing of nuclear, chemical, or biological weapons or missile
 technology products (mass destruction weapons). Product and related software and technology may be controlled under the
 Japanese Foreign Exchange and Foreign Trade Law and the U.S. Export Administration Regulations. Export and re-export of Product
 or related software or technology are strictly prohibited except in compliance with all applicable export laws and regulations.
- Please contact your TOSHIBA sales representative for details as to environmental matters such as the RoHS compatibility of Product. Please use Product in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. TOSHIBA assumes no liability for damages or losses occurring as a result of noncompliance with applicable laws and regulations.