


## **QPL (Dummy Load) Terminations**

## 2001/2002 Series

V2.00

312 HEX. (7.9) SMA PLUG (6.4) (6.4) (6.4)

38







.250 HEX.

(6.4)







42	

Military Part Number	M/A-COM Part Number	Outline	Dim. A Inches (mm	Commercial ) Alternate
-01	2001-4178-00N	38	.520 (13	.2) <b>2001-6112-00</b>
-02	2001-4182-02N	38	.520 (13	.2) <b>2001-6112-02</b>
-03	2001-4173-00N	39	_	_
-04	2001-4173-02N	39		_
-05	2002-4065-00N	40	_	2002-6112-00
-06	2002-4065-02N	40	_	2002-6112-02
-07	2002-4066-00N	41	-	_
-08	2002-4066-02N	41		_
-09	2001-4302-00N	38	.520 (13	.2) <b>2001-6111-00</b>
-10	2001-4303-00N	38	.520 (13	.2) —
-11	2001-4301-00N	42		2003-6117-00
-12	2001-4294-00N	38	.550 Max. (14	.0) <b>2001-6110-00</b>
-13	2001-4304-00N	39		-
-15	2001-4305-00N	38	.520 (13	.2) <b>2001-6116-00</b>

Screened and Non-screened units are available. Suffix N is a non-screened QPL device. For a screened QPL device change the N to S.

M/A-COM Division of AMP Incorporated North America: Tel. (800) 366-2266, Fax (800) 618-8883 Asia/Pacific: Tel. +85 2 2111 8088, Fax +85 2 2111 8087 Europe: Tel. +44 (1344) 869 595, Fax +44 (1344) 300 020

Specifications subject to change without notice.



3-12