
Series 91 and 92 Miniature Broadband SP3T Switches

- Frequency range (Series 91): 1 to 18 GHz
- Frequency range (Series 92): 0.2 to 4 GHz
- · Rise and fall times as fast as 10 nsec
- · Reflective and nonreflective models
- Low VSWR and insertion loss
- Isolation: up to 60 dB
- · Miniature size, light weight



9130-500 (DRIVERLESS)



F9130 (WITH INTEGRATED DRIVER)

MODELS 9130-500 AND 9230-500

These switches provide high-performance characteristics over a multi-octave frequency range. The Model 9130-500 covers the 1 to 18 GHz frequency range while the Model 9230-500 covers the 0.2 to 4 GHz range. This description and operation are the same as that for the Models 9120-500 and 9220-500 SP2T switches.

MODELS 9130T-500, 9130W-500 AND 9230T-500

These switches are non-reflective versions of the switches described above.

MODELS 9130AH-500 AND 9130AHT-500

These switches are the same as the 9120AH-500 and 9120AHT-500 except for the number of ports.

SERIES F91 AND F92

The Series F91 and F92 switches are the same as the corresponding Series 91 and 92 models, except the units are equipped with integrated drivers.

SERIES G91 AND G92

These switches are the same as the Series G91 and G92 SP2T switches except for the number of ports.



Series 91 and 92 SP3T Switches Specifications

MODEL NO. (1)	CHARACTERISTIC	FREQUENCY (GHz)					
		0.2-1	1-2	2-4	4-8	8-12.4	12.4-18
9130-500 F9130	Min Isolation (dB) Max Insertion Loss (dB) Max VSWR (ON)		60 1.5 1.75	60 1.5 1.75	60 1.5 1.75	60 2.0 1.75	50 2.5 2.0
G9130	Min Isolation (dB) Max Insertion Loss (dB) Max VSWR (ON)		60 1.8 1.5	60 1.8 1.5	60 2.0 1.7	60 2.5 1.7	50 2.8 2.0
9230-500 F9230	Min Isolation (dB) Max Insertion Loss (dB) Max VSWR (ON)	60 1.5 1.5	60 1.5 1.5	60 1.5 1.5	- -		=
G9230	Min Isolation (dB) Max Insertion Loss (dB) Max VSWR (ON)	60 1.8 1.5	60 1.8 1.5	60 1.8 1.5	•	=	- - -
9130T-500 F9130T G9130T	Min Isolation (dB) Max Insertion Loss (dB) Max VSWR (ON or OFF)		50 1.4 1.5	50 1.4 1.5	45 1.6 1.7	40 1.8 1.7	40 2.5 2.0
9230T-500 F9230T G9230T	Min Isolation (dB) Max Insertion Loss (dB) Max VSWR (ON or OFF)	60 1.2 1.5	60 1.2 1.5	50 1.4 1.5	•	=	Ţ
9130W-500 F9130W G9130W	Min isolation (dB) Max insertion Loss (dB) Max VSWR (ON or OFF)		60 1.8 1.5	60 1.8 1.5	60 2.0 1.7	60 2.5 1.7	55 24 20
9130AH-500 F9130AH	Min Isolation (dB) Max Insertion Loss (dB) Max VSWR (ON)	. + -	60 1.2 1.75	60 1.2 1.75	60 1.5 1.75	60 2.0 1.75	50 2.6 2.0
9130AHT-500 F9130AHT	Min Isolation (dB) Max Insertion Loss (dB) Max VSWR (ON) Max VSWR (OFF)		60 1.6 1.75 1.75	60 1.6 1.75 1.75	60 1.8 1.9 2.0	60 2.5 2.0 2.2	50 3.3 2.0 2.3

PERFORMANCE CHARACTERISTICS

Power Handling Capability

Without Performance Degradation
Units without "T" or "W" suffix: 1W cw or peak
Units with "T" or "W" suffix
Input to any "OFF" port: 100 mW cw or peak
Input to any "ON" port: 1W cw or peak
Input to common port: 1W cw or peak

Survival Power
Units without "T" or "W" suffix: 1W average,
75W peak (1 µsec max. pulse width)
Units with "T" or "W" suffix
Input to any "OFF" port: 1W average,
10W peak (1 µsec max. pulse width)
Input to any "ON" port: 1W average,
75W peak (1 µsec max. pulse width)
Input to common port: 1W average,
75W peak (1 µsec max. pulse width)



⁽¹⁾ Models prefixed with "F" or "G" are equipped with integrated TTL-compatible drivers; models without the "F" or "G" prefix are current-controlled units and are furnished without drivers; models suffixed with "T" or "W" are non-reflective except a high VSWR will be present at the common port if all other ports are OFF; models suffixed with "H" are high-speed units.

Series 91 and 92 SP3T Switches Specifications

Switching Characteristics® SERIES 91/92/F91/F92

Units without "H" suffix

ON time 500 nsec max.

OFF time 500 nsec max.

Units with "H" suffix

SERIES G91/G92

Power Supply Requirements

SERIES 91/92/F91/F92

Driverless Units

Bias current required at each port for rated isolation and insertion loss

Port OFF

Units without "H" suffix +50 mA
Units with "H" suffix +30 mA
Port ON
Units without "H" suffix -50 mA
Units with "H" suffix -35 mA

Units With Integrated Drivers

(For one port ON)

(i or one port ort)	+5V ±5%	-12 to -15V
Units Without "H" Suffix	130 mA	60 mA
Units With "H" Suffix	75 mA	55 mA
Units With "HT" Suffix	105 mA	55 mA

SERIES G91/G92 (For one port ON)

+5V ±5%, 100 mÅ

Control Characteristics

SERIES 91/92/F91/F92

Units With Integrated Drivers

Control Input Impedance

Units without "H" suffix . . . TTL, low power Schottky, one

unit load. (A unit load is 0.8 mA sink current and 40 vA source

current.)

Units with "H" suffix TTL, advanced Schottky, one

unit load. (A unit load is 0.6 mA sink current and 20 μ A source

current.)

Control Logic Logic "0" (-0.3 to +0.8 V) for

port ON and logic "1" (+2.0 to

+5.0 V) for port OFF.

SERIES G91/G92

Control Input Impedance. . Schottky TTL, one unit load.

(A unit load is 2.0 mA sink current and 50 μA source

current.)

Control Logic Logic "0" (-0.3 to +0.8 V)

for port ON and logic "1"

(+2.0 to +5.0 V) for port OFF.



 $⁺¹⁵V \pm 5\%$, 40 mA

For driverless units, shaped current pulses must be provided by user.

Series 91 and 92 SP3T Switches Specifications

ENVIRONMENTAL RATINGS

Temperature Range

Units With Integrated Drivers

Operating -65° C to $+110^{\circ}$ C Non-Operating - 65°C to + 125°C

Driverless Units Operating and

Humidity MIL-STD-202F, Method 103B,

Cond. B (96 hrs. at 95%)

MIL-STD-202F, Method 213B,

Cond. B (75G, 6 msec)

MIL-STD-202F, Method 204D,

Cond. B (.06" double amplitude or 15G, whichever is less)

Altitude MIL-STD-202F, Method 105C,

Cond. B (50,000 ft.)

Temp. Cycling MIL-STD-202F, Method 107D,

Cond. A, 5 cycles

AVAILABLE OPTIONS

Option No.	Description			
3	SMA female bias/control connectors			
7	SMA male rf connectors			
9	Inverse control logic; logic "0" for			
	port OFF and logic "1" for port ON (Not applicable to Series 91/92)			
33	EMI-filter solder-type			
	bias/control terminals			
41*	Internal video filter, common port only			
42*	Internal video filter, output ports only			
43*	Internal video filter, all ports			
64A	SMB male bias/control connectors			

*Not applicable to Series 92/F92/G92. See chart following the power handling discussion on page 98.

